

---

---

## CRAZY WAP & MMS Setup

The setup of WAP and MMS on your DUALSIM Mobile Phone is carried out in 3 stages.

- GPRS Data Account Setup
- WAP Setup
- MMS Setup

### Step 1 – GPRS DATA Account Setup

1. Go to the following menu “MENU > SERVICES > DATA ACCOUNT > GPRS > *Select an empty Account*”
2. Edit the following parameters in the account
  - a. Account Name = **CRAZY WAP GPRS**
  - b. APN = purtona.wap
  - c. User name = [blank]
  - d. Password = [blank]
  - e. Auth. Type = *Normal*
3. Exit back to MAIN SCREEN.

### Step 2 – WAP Setup

1. Go to the following menu “MENU > SERVICES > WAP > SETTINGS > EDIT PROFILE > SIM 1 or 2 > *Select an empty PROFILE > EDIT PROFILE*”
2. EDIT the following parameters in the account
  - a. Rename Profile = *CRAZY WAP*
  - b. Homepage = *http://crazyjohns.mobi/*
  - c. Data Account = **CRAZY WAP GPRS**
  - d. Connection Type = *HTTP*  
*Proxy Address = 010.202.002.020*  
*Proxy Port = 8080*
  - e. User Name = [blank]
  - f. Password = [blank]
3. BACK then ACTIVATE PROFILE and exit back to the MAIN SCREEN.
4. Your Phone is ready to access WAP and MMS services.

### Step 3 – MMS Setup

1. Go to the following menu “MENU > MESSAGES > MMS > MMS SETTINGS > SERVER PROFILE > SIM 1 or 2 > *Select an empty Account*”
2. EDIT the following parameters in the account
  - a. Rename Profile = *CRAZY MMS*
  - b. Homepage = *http://purtona.mms/mmssend*
  - c. Data Account = **CRAZY WAP GPRS**
  - d. Connection Type = *HTTP*  
*Proxy Address = 010.202.002.020*  
*Proxy Port = 8080*
  - e. User Name = [blank]
  - f. Password = [blank]
3. BACK then ACTIVATE PROFILE and exit back to the MAIN SCREEN.
4. Your Phone is ready to access WAP and MMS services.