

---

---

## **OPTUS PRE-PAY WAP & MMS Setup**

The setup of WAP and MMS on your DUALSIM Mobile Phone is carried out in 4 stages.

- MMS Data Account Setup
- MMS Setup
- WAP Data Account Setup
- WAP Setup

### **Step 1 – MMS Data Account Setup**

1. Go to the following menu “MENU > SERVICES > DATA ACCOUNT > GPRS > *Select an empty Account*”
2. Edit the following parameters in the account
  - a. Account Name = **OptusMMSGPRS**
  - b. APN = *mms*
  - c. User name = [blank]
  - d. Password = [blank]
  - e. Auth. Type = *Normal*
3. Exit back to MAIN SCREEN.

### **Step 2 – MMS Setup**

1. Go to the following menu “MENU > MESSAGES > MMS > MMS SETTINGS > SERVER PROFILE > SIM 1 or 2 > *Select an empty Account*”
2. EDIT the following parameters in the account
  - a. Rename Profile = *Optus MMS*
  - b. Homepage = *http://mmsc.optus.com.au:8002*
  - c. Data Account = **OptusMMSGPRS**
  - d. Connection Type = *WAP*  
*Proxy Address = 061.088.190.010*
  - e. User Name = [blank]
  - f. Password = [blank]
3. BACK then ACTIVATE PROFILE and exit back to the MAIN SCREEN.
4. Your Phone is ready to access WAP and MMS services.

---

---

### **Step 3 – WAP Data Account Setup**

1. Go to the following menu “MENU > SERVICES > DATA ACCOUNT > GPRS > *Select an empty Account*”
2. Edit the following parameters in the account
  - a. Account Name = **OptusWAPGPRS**
  - b. APN = *prepaidyesoptus*
  - c. User name = [blank]
  - d. Password = [blank]
  - e. Auth. Type = *Normal*
3. Exit back to MAIN SCREEN.

### **Step 4 – WAP Setup**

1. Go to the following menu “MENU > SERVICES > WAP > SETTINGS > EDIT PROFILE > SIM 1 or 2 > *Select an empty PROFILE > EDIT PROFILE*”
2. EDIT the following parameters in the account
  - a. Rename Profile = *Optus WAP*
  - b. Homepage = *http://networker.optus.net.au/wap/index.wml*
  - c. Data Account = **OptusWAPGPRS**
  - d. Connection Type = *WAP*  
*Proxy Address = 202.139.083.152*
  - e. User Name = [blank]
  - f. Password = [blank]
3. BACK then ACTIVATE PROFILE and exit back to the MAIN SCREEN.
4. Your Phone is ready to access WAP and MMS services.