
SOUL/TPG WAP & MMS Setup

The setup of WAP and MMS on your DUALSIM Mobile Phone is carried out in 4 stages.

- MMS Data Account Setup
- MMS Setup
- WAP Data Account Setup
- WAP Setup

Step 1 – MMS Data Account Setup

1. Go to the following menu “MENU > SERVICES > DATA ACCOUNT > GPRS > *Select an empty Account*”
2. Edit the following parameters in the account
 - a. Account Name = **SOULTPGMMS**
 - b. APN = *mms*
 - c. User name = [blank]
 - d. Password = [blank]
 - e. Auth. Type = *Normal*
3. Exit back to MAIN SCREEN.

Step 2 – MMS Setup

1. Go to the following menu “MENU > SERVICES > WAP > SETTINGS > EDIT PROFILE > SIM 1 or 2 > *Select an empty PROFILE > EDIT PROFILE*”
2. EDIT the following parameters in the account
 - a. Rename Profile = *SoulTPG MMS*
 - b. Homepage = *http://mmsc.optus.com.au:8002/*
 - c. Data Account = **SOULTPGMMS**
 - d. Connection Type = *WAP*
Proxy Address = 061.088.190.010
 - e. User Name = [blank]
 - f. Password = [blank]
3. BACK then ACTIVATE PROFILE and exit back to the MAIN SCREEN.
4. Your Phone is ready to access WAP and MMS services.

Step 3 – WAP Data Account Setup

1. Go to the following menu "MENU > SERVICES > DATA ACCOUNT > GPRS > *Select an empty Account*"
2. Edit the following parameters in the account
 - a. Account Name = **SOULTPGWAP**
 - b. APN = *wap.optus.net.au*
 - c. User name = [blank]
 - d. Password = [blank]
 - e. Auth. Type = *Normal*
3. Exit back to MAIN SCREEN.

Step 4 – WAP Setup

1. Go to the following menu "MENU > MESSAGES > MMS > MMS SETTINGS > SERVER PROFILE > SIM 1 or 2 > *Select an empty Account*"
2. EDIT the following parameters in the account
 - a. Rename Profile = *SoulTPG*
 - b. Homepage = *http://networker.optus.net.au/wap/index.wml*
 - c. Data Account = **SOULTPGWAP**
 - d. Connection Type = *WAP*
Proxy Address = 202.139.083.152
 - e. User Name = [blank]
 - f. Password = [blank]
3. BACK then ACTIVATE PROFILE and exit back to the MAIN SCREEN.
4. Your Phone is ready to access WAP and MMS services.