
VIRGIN WAP & MMS Setup

The setup of WAP and MMS on your DUALSIM Mobile Phone is carried out in 4 stages.

- WAP Data Account Setup
- WAP Setup
- MMS Data Account Setup
- MMS Setup

Step 1 – WAP DATA Account Setup

1. Go to the following menu “MENU > SERVICES > DATA ACCOUNT > GPRS > *Select an empty Account*”
2. Edit the following parameters in the account
 - a. Account Name = **VIRGIN WAP GPRS**
 - b. APN = *virginwap*
 - c. User name = [blank]
 - d. Password = [blank]
 - e. Auth. Type = *Normal*
3. Exit back to MAIN SCREEN.

Step 2 – WAP Setup

1. Go to the following menu “MENU > SERVICES > WAP > SETTINGS > EDIT PROFILE > SIM 1 or 2 > Select an empty PROFILE > EDIT PROFILE”
2. EDIT the following parameters in the account
 - a. Rename Profile = *VIRGIN WAP*
 - b. Homepage = *http://www.virginvibe.com.au/wap/*
 - c. Data Account = **VIRGIN WAP GPRS**
 - d. Connection Type = *WAP*
Proxy Address = 202.139.083.152
 - e. User Name = [blank]
 - f. Password = [blank]
3. BACK then ACTIVATE PROFILE and exit back to the MAIN SCREEN.
4. Your Phone is ready to access WAP and MMS services.

Step 3 – MMS DATA Account Setup

1. Go to the following menu "MENU > SERVICES > DATA ACCOUNT > GPRS > *Select an empty Account*"
2. Edit the following parameters in the account
 - a. Account Name = **VIRGIN MMS GPRS**
 - b. APN = *VirginMMS*
 - c. User name = [blank]
 - d. Password = [blank]
 - e. Auth. Type = *Normal*
3. Exit back to MAIN SCREEN.

Step 4 – MMS Setup

1. Go to the following menu "MENU > MESSAGES > MMS > MMS SETTINGS > SERVER PROFILE > SIM 1 or 2 > *Select an empty Account*"
2. EDIT the following parameters in the account
 - a. Rename Profile = *VIRGIN MMS*
 - b. Homepage = *http://mms.virginvibe.com.au:8002/*
 - c. Data Account = **VIRGIN MMS GPRS**
 - d. Connection Type = *HTTP*
Proxy Address = 202.139.083.152
 - e. User Name = [blank]
 - f. Password = [blank]
3. BACK then ACTIVATE PROFILE and exit back to the MAIN SCREEN.
4. Your Phone is ready to access WAP and MMS services.